



ADS 120D MEDIA / 100V LINE 120W MIXER AMPLIFIER

Features:

- Rated power 120W, 100V speaker output
- Digital amplifier module, high efficiency (85%)
- Built-in USB & Bluetooth module
- 2 AUX & 2 Mic inputs & 1 AUX output
- Each AUX & Mic input with individual volume control
- Mic 1 of 6.35mm in front panel, with priority & muting
- With priority input and 100V input
- 1 U compact design, space and cost saving

TECHNICAL SPECIFICATIONS

Rated Power	120W RMS
Speaker Output	100V
Mic	0.006 VRMS
Line	0.3 VRMS
SNR	MIC ≥ 74 db(Maximum) AUX ≥ 80 dB (Maximum)
Frequency Response	80Hz-15kHz (± 3 dB)
Distortion	$\leq 0.5\%$
Power Supply	AC220V - 240V, 50-60Hz,
Tone	Bass ± 10 dB (100Hz) Treble ± 10 dB (10kHz)
Power Consumption	150W
Size (WxDxL)	W200xD190xH44mm
Net Weight	1.5kg
Gross Weight	2kg